

MARK SERIES HIGH INTENSITY DMX CONTROL STROBES



3 MODELS FEATURING

- 9 ULTRA BRIGHT HYPER FLASH MODES, WITH HYPER BLASTER
- 1-60 Flashes/second on 1 Channel, Fixed Intensity Blaster; No Step Down
 - 1-20 Flashes/second on 2 Channel Mode; Variable Rate & Intensity
 - 1-12 Flashes/second Stand Alone on Unit Rotary Pot Adjustment

ANALOG OR DMX OPERATION - SHOW CONTROL CAPABLE

2 FIELD, WIDE & NARROW - CERAMIC LAMP MOUNT

MARK 2000 (0432)

95-120 V, 15 Amp, 50/60 Hz
2000 Watt Avg. Strobe Mode
12K Peak Hyper Mode
Lamp Life - 10 million flashes

MARK 3600 (0416)

205-240 V, 20 Amp, 50/60 Hz
3600 Watt Avg. Strobe Mode
30K Peak Hyper Mode
Lamp Life - 5 million flashes

MARK 5000 (0427)

DISCONTINUED

ACCESSORIES

SK-XLR - Striker Remote - 0422 - Analog, Models - MARK 2000, 3600 & 5000
SR-DMX - Strobe Runner - 0483 - 120V - MARK 2000
SR-DMX - Strobe Runner - 0484 - 240V - MARK 3600 & 5000

Linear Lamp - 0433 (MARK 2000); 0411 & 0459 (MARK 3600); - 0415 (MARK 5000)

MECHANICAL

Model 0432 - 16.00" (40.6 cm) Wide X 7.0" (17.8 cm) High X 7" (17.8 cm) Deep; Weight 9 lbs. (4.1 kg)
Model 0416 - 19.75" (50.2 cm) Wide X 8.5" (21.6 cm) High X 8" (20.3 cm) Deep; Weight 12 lbs. (5.45 kg)
Model 0427 - 22.50" (57.2 cm) Wide X 8.5" (21.6 cm) High X 8" (20.3 cm) Deep; Weight 15 lbs. (6.8 kg)

United States Patent No. 6,271,634 (MARK 3600 & MARK 5000)